



HONDAPETRO

Generator

Models	HONDAPETRO HP3000GX
Frequency (Hz)	50
Rated voltage (V)	230 V
Number of phases	Single phase
Rated Output (KW)	3,0
Max. Output (KW)	3,3
DC Output (V/A)	12/8.3
Over Current Protector	YES
Engine Model	GX290
Engine displacement (cc)	290
Engine speed (Rpm)	3000
Engine Type	Single-cylinder, four-stroke, air-cooled, gasoline engine
Fuel type	Gasoline
Cooling method	Air cooled
Fuel Tank Capacity (L)	20L
Oil Capacity (L)	1.1L
Continuous Running Time (H)	8
Starting System	Electric start + Recoil (manual) start
Battery (V)	12
Other configurations (Optional)	ATS fully automatic
	RS485 interface
	4G remote module
	Remote start
Dimension (LxWxH)(cm)	59×49×44
Dry Weight (kg)	45

