



HONDAPETRO

Generator

Models	HONDAPETRO HP5000GX
Frequency (Hz)	50
Rated voltage (V)	230 V
Number of phases	Single phase
Rated Output (KW)	5,0
Max. Output (KW)	5,5
DC Output (V/A)	12/8.3
Over Current Protector	YES
Engine Model	GX420
Engine displacement (cc)	420
Engine speed (Rpm)	3000
Engine Type	Single-cylinder, four-stroke, air-cooled, gasoline engine
Fuel type	Gasoline
Cooling method	Air cooled
Fuel Tank Capacity (L)	25L
Oil Capacity (L)	1.1L
Continuous Running Time (H)	8-10
Starting System	Electric start + Manual start
Battery (V)	12
Dimension (LxWxH)(cm)	695×520×555
Dry Weight (kg)	82

